

## Technical Data

number of pins	9
power	4 (3+PE)
signal	5
temperature range	-20 °C to 130 °C
clamping range	Ø 9,5 mm to Ø 14,5 mm
protection type	when connected IP 66/67

## Electrical Data

rated current	<b>power</b> max. 30 A*	<b>signal</b> max. 7 A*
rated voltage	630V (AC/DC)	250 V (AC/DC)
rated insulation voltage (L-L)	6000 V	2500 V

mating cycles	500
---------------	-----

## Data according to VDE 0110/EN61984, Paragraph 6.19.2.2

pollution degree	3
over voltage category	III
max. height for operation	2000 m

## Material

housing	zinc diecast / nickel plated
insulation insert	PA 6.6 mod., UL 94/V0
seals	FKM
contacts	brass / gold plated
contacts	brass / gold plated
clamp ring	brass / nickel plated

## Contacts

Item:	60.302.11
type	Contact Socket 2.0 mm
cross section	crimp/ 2.50 - 4.00 mm <sup>2</sup>
contact resistance	< 3 mOhm

Item:	60.001.11
type	Contact Socket 1.0 mm
cross section	crimp/ 0.14 - 1.00 mm <sup>2</sup>
contact resistance	< 5 mOhm

## Tools (not part of product contents)

digital crimping tool for 1mm-/2 mm- contacts  
Item: C0.236.00

analog crimping tool for 1 mm-/2 mm- contacts  
Item: C0.201.00

positioning insert for ø2mm contacts  
Item: C0.004.00

## B ST A 200 FR 32 42 0100 A00



## Contact Arrangement

mating view




## Contact Socket 2.0 mm

crimp/ 2.50 - 4.00 mm<sup>2</sup>  
Item: 60.302.11



## Contact Socket 1.0 mm


crimp/ 0.14 - 1.00 mm<sup>2</sup>  
Item: 60.001.11



Copyright by Electro-Matic Integrated, INC.  
All rights, including rights created by patent grant or registration  
of a utility model or design, are reserved.  
Noncompliance will result in seeking damages.

This document is for information only and before utilization  
the user must reconfirm actuality.  
Subject to technical changes.

Electro-Matic Integrated, INC.  
23410 Industrial Park Court  
48335 Farmington Hills, MI  
USA  
E-Mail: ConnectivityEng@electro-matic.com  
Web: www.emintegrated.com



## Main Dimensions

Plug

\*for max. wire cross-section  
pay attention to the  
cross-section of used contacts